

# Experiences from developing a Wi-Fi HaLow shield for an ESP32 Board

## 3rd Wi-Fi HaLow in Europe Workshop, Bern

ZHAW Institute of Signal Processing and Wireless Communications, CH-8401 Winterthur

Stefan Lindemann, Lukas Thomi, Luciano Sarperi


06.02.2026



## Develop the first EU-compatible Wi-Fi HaLow shield for ESP32

- Develop hardware of shield based on **Newracom WHM500A** Wi-Fi HaLow Module with **NRC7394** SoC to assess **Wi-Fi HaLow performance and energy consumption** in a realistic embedded setting
- Develop set of simple **AT-Command Wrappers** (for simple implementation of own Test-Applications on ESP32 in C running on FreeRTOS)
- Develop **test application / functions** (periodic data transmission, throughput test) based on AT-Command Wrappers

ESP32-DEVKITC-VE  
(ESP32-WROVER-E)




# Background

- In [1] we tested the **Wi-Fi HaLow Performance** under EU/CH regulatory restrictions with the Newracom Eval-Kit (Raspberry Pi) at **1 MHz Channel-Bandwidth**
- Maximum data throughput: **2.3 Mbit/s**
- With **duty-cycle (DC) limitation of 2.8 %** for STA maximum mean data throughput: **64 kbit/s**
- Range Indoor: **3 Floors** (130 kbit/s without DC limitation)
- Range urban outdoor: **230 m** (110 kbit/s without DC limitation)
- Wi-Fi HaLow shield developed in this project uses ESP32 → No Driver available, must use AT-commands




Newracom WHM500A EVK

# Wi-Fi HaLow Shield for ESP32: Block Diagram




# Wi-Fi HaLow Shield for ESP32: Hardware



## Execution of wrappers and AT commands

- The AT-Engine task handles the AT commands, there is only one task instance
- Multiple tasks may use AT-Command wrappers simultaneously. The **AT-Engine ensures** that the **AT commands** associated with the AT command wrappers **are not interrupted**



# AT-Command Wrappers



## Implemented AT-Command Wrappers

### Read status of WHM module

halow\_at\_status

### Set baudrate und flow control

halow\_at\_uart

### Scan Wi-Fi networks

halow\_scan\_wifi

### Set and read IPv4 configuration

halow\_set\_ipv4\_config

halow\_get\_ipv4\_config

### Set, read and terminate Wi-Fi connection

halow\_set\_wifi\_connection

halow\_get\_wifi\_connection

halow\_disconnect\_wifi

### Set and read country code

halow\_set\_country\_code

halow\_get\_country\_code

### Set and read transmit power

halow\_set\_duty\_cycle

halow\_get\_duty\_cycle

### Configure AP mode

halow\_setup\_soft\_ap

### Read RSSI and SNR

halow\_get\_wifi\_rssi

### TCP socket functions

halow\_create\_tcp\_socket

halow\_connect\_to\_tcp\_socket

halow\_close\_all\_sockets

halow\_send\_tcp\_data

### Timeout settings

halow\_set\_wifi\_timeout

halow\_set\_socket\_timeout

## Implemented high-level Test Functions (do not respect duty-cycle limits)

- TCP data transmission test: TCP Packet (32 Bytes) sent every 200 ms
- TCP throughput test: Continuous TCP Packet transmission (1024 Bytes), limited to 1 Mbit/s (see later)

## Implemented Management Functions

- Automatic Wi-Fi connection setup and re-establishment
- Passthrough mode for use of AT-CMD tool from Newracom (Graphical UI for AT-Command use) via ESP32


# Link-Budget Test

## Maximum coupling loss $L_{\max}$ between TX and RX

- $f_c = 863.5$  MHz, BW = 1 MHz
- $P_{\text{tx\_max}} = 14$  dBm, adaptive (auto mode)
- Transmission over Cable with attenuation, running TCP throughput test

Measured maximum coupling loss  $L_{\max} = 112$  dB ( $P_{\text{rx\_min}} = -98$  dBm)

Sanity check: In [1]  $P_{\text{rx\_min}} = -101$  dBm  $\rightarrow$  ok



# Throughput Test under 'ideal' Conditions

- **TCP Throughput (AP and STA in close proximity)**
  - $f_c = 863.5$  MHz, BW = 1 MHz
  - Data transfer with 2 MBaud/s UART (transmitter and receiver)
  - Receiver determines throughput
  - Test results: Similar **throughput of 1 MBit/s** as in tests with **Newracom EVK** when using AT Commands over UART with 2 MBaud/s

```
[INFO AT Task] UART Throughput: 1040256.00 bits/sec  
[INFO AT Task] UART Throughput: 998976.00 bits/sec  
[INFO AT Task] UART Throughput: 1006528.00 bits/sec  
[INFO AT Task] UART Throughput: 998592.00 bits/sec  
[INFO AT Task] UART Throughput: 1019456.00 bits/sec  
[INFO AT Task] UART Throughput: 993600.00 bits/sec  
[INFO AT Task] UART Throughput: 1026432.00 bits/sec  
[INFO AT Task] UART Throughput: 994624.00 bits/sec  
[INFO AT Task] UART Throughput: 1017472.00 bits/sec  
[INFO AT Task] UART Throughput: 1007808.00 bits/sec  
[INFO AT Task] UART Throughput: 998976.00 bits/sec
```




# Limitations in Throughput Testing

## TCP Throughput speed limitation of 1 Mbit/s due to UART at 2 MBaud/s

- Maximum UART speed of 2 MBaud/s for exchange of AT-Commands between ESP32 and WHM500A limits achievable Wi-Fi HaLow throughput
- UART Hardware Flow Control (HFC) used
- Alternative: Use of SPI for AT-Command transfer (not implemented)

# Throughput and Range Test in Building: Same Floor



Mobile STA



$$f_c = 863.5 \text{ MHz}, \text{ BW} = 1 \text{ MHz}$$

# Throughput and Range Test in Building: Across Floors



$$f_c = 863.5 \text{ MHz}, \text{ BW} = 1 \text{ MHz}$$

# References

- [1] T. Barnes, V. Phimmasane, L. Sarperi, "Results from Tests with the Newracom NRC7394 Wifi HaLow SoC", 2nd Wifi HaLow in Europe Workshop, 22.01.2025, ZHAW, Winterthur, [https://www.zhaw.ch/storage/engineering/institute-zentren/isc/Dateienablage\\_News/ZHAW\\_WiFi\\_HaLow\\_ISC\\_InEs\\_22.01.2025\\_V2.pdf](https://www.zhaw.ch/storage/engineering/institute-zentren/isc/Dateienablage_News/ZHAW_WiFi_HaLow_ISC_InEs_22.01.2025_V2.pdf)

